
LED Up Lights



Created for small scale elements, the CC combines smart style and function. Our Driver-On-Board technology uses long-life LEDs to provide excellent illumination. The CC fuses a progressive design with precision engineering, making it an ideal selection.

CC: Up Light

NUMBER OF LEDS:	1	3
HALOGEN LUMEN OUTPUT EQUIVALENT:	10 Watt	20 Watt
USEFUL LED LIFE (L70):	50,000 hrs avg	50,000 hrs avg
INPUT VOLTAGE:	10 to 15V	10 to 15V
VA TOTAL: (Use this number to size the transformer)	2.4	4.5
WATTS USED:	2.0	4.2
LUMENS PER WATT (EFFICACY)	35.8	28.2
MAX LUMENS:	59	123
CCT (Ra)	69.3	69.3





FACTORY INSTALLED OPTIONS: Order 1 + 2 (optional) + 3 + 4 (optional) + 5

Step	Description	Code
1	FIXTURE	CC
2	OPTIONAL ZD	ZD (Refer to the Luxor page in the Lighting Control section)
3	LAMP	1LED, 3LED (50,000 avg. life hours)
4	OPTIONAL SHIELD	LS (Long shield)
5	FINISH	AB*, AT*, NP*, BS

EXAMPLE: CC-ZD-1LED-AB = CC - ZD Option - 1LED Board - Antique Bronze Finish

FIELD INSTALLED OPTIONS: Order Individually

Mounts	Beam Angle Lenses		
Long Slot Spike (Included) (250015840000) 2.5" x 10"	LENS OPTIONS	1LED	3LED
Super Slot Spike (753900) 2" x 10"	Diffuser 18° (preassembled)	770600	771300
SuperJ-Box (SJ-XX**) 2.5" x 12"	Flood Lens 30-32° (1 notch)	1LEDFLLENS	3LEDFLLENS
Post Mount (PM-XX**) 2.5" x 13"	Wide Flood Lens 56-58° (2 notches)	1LEDWFLLENS	3LEDWFLLENS

EXAMPLE: 753900 = Super Slot Spike

PHOTOMETRICS:



Beam angle is calculated using LM-79 method for SSL Luminaires:

METALS AB = Antique Bronze* (On Brass) AT = Antique Tumbled* (On Brass) NP = Nickel Plate*

BS = Natural Brass

The CC includes choice of LED board, your choice of finish, 4 ft lead wire and a Long Slot Spike.



All CC up lights come standard with amber, green, blue and frosted filters

* May require longer lead time

** Denotes finish code



[&]quot;Beam angle is defined as two times the vertical angle at which the intensity is 50% of the maximum."