




*The JB is FX Luminaire's original LED down light. The JB solves the problem of changing lamps in complicated areas by providing long-life LEDs. The pure color of the LED allows you to add the supplied blue lens to create a natural moonlight effect.*

## JB: Down Light

NUMBER OF LEDS:	1	3
HALOGEN LUMEN OUTPUT EQUIVALENT:	10 Watt	20 Watt
USEFUL LED LIFE (L70):	50,000 hrs avg	50,000 hrs avg
INPUT VOLTAGE:	10 to 15V	10 to 15V
VA TOTAL: (Use this number to size the transformer)	2.4	4.5
WATTS USED:	2.0	4.2
LUMENS PER WATT (EFFICACY)	23.9	30
MAX LUMENS:	50	127
CCT (Ra)	69.4	66.9





# JB: Down Light

**FACTORY INSTALLED OPTIONS: Order 1 + 2 + 3**

FIXTURE CODE	LAMP CODE	MOUNTING CODE	FINISH OPTIONS
<b>1</b> JB	<b>2</b> 1 LED (50,000 avg. life hours)	<b>3</b> WM (Wall mount)	<b>3</b> XX
	3 LED (50,000 avg. life hours)		(see options to right)

The JB includes your choice of 1LED or 3LED board and choice of finish and 26 ft. lead wire.

**FIELD INSTALLED OPTIONS: Order Individually**

**MOUNTING OPTIONS**

<b>A</b> TB (Tree Box, X" x X" x X")	  
VB-050 (VersaBox, 2.5" x 2")	
MJ-050 (Mini J-Box, 3.5" x 2.125" x 1.32")	

**EXAMPLE: JB-3LED-WM-BZ = JB - 3 LEDs - Wall Mount - Bronze Metallic Finish**  
**VB-050 = VersaBox**

**POWDERCOAT**

	WG = White Gloss
	FW = Flat White
	AL = Almond
	BZ = Bronze Metallic
	DG = Desert Granite
	WI = Weathered Iron
	VF = Verde Speckle
	SB = Sedona Brown
	FB = Flat Black

**PHOTOMETRICS:**



For information on ZD technology please refer to the Luxor page in the Lighting Control section.

All JB down lights come standard with amber, green, blue and frosted filters

\*\* Denotes powdercoat finish